



SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.

CE EMC REPORT

Prepared For :	SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD. 5th Floor B3, B1 B2 B3 Building, 2nd Nanchang Industrial Park, Xixiang Street, Baoan District, Shenzhen, China
Product Name:	INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY
Model :	PS300-H1VXX,PS250-H1VXX, PS200-H1VXX (XX Stands for DC Output Voltage 05,12,24,36,48)
Prepared By :	Shenzhen BST Technology Co., Ltd. Building No.23-24, Zhiheng Industrial Park, Guankouer Road, Nantou,Nanshan District,Shenzhen,Guangdong,China
Test Date:	Sep. 14-18, 2017
Date of Report :	Sep. 18, 2017
Report No.:	BSTDG1709996200008ER-1



TABLE OF CONTENTS

TEST REPORT DECLARATION.....	5
1. TEST RESULTS SUMMARY.....	7
2. GENERAL INFORMATION.....	8
2.1. Report information.....	8
2.2. Measurement Uncertainty.....	8
3. PRODUCT DESCRIPTION.....	9
3.1. EUT Description.....	9
3.2. Block Diagram of EUT Configuration.....	9
3.3. Operating Condition of EUT.....	9
3.4. Test Conditions.....	9
3.5. Modifications.....	9
3.6. Abbreviations.....	10
3.7. Performance Criterion.....	10
4. TEST EQUIPMENT USED.....	11
4.1. For Conducted Emission Test.....	11
4.2. For Radiated Emission Measurement.....	11
4.3. For Harmonic / Flicker Test.....	11
4.4. For Electrostatic Discharge Immunity Test.....	11
4.5. For RF Strength Susceptibility Test.....	11
4.6. For Electrical Fast Transient/Burst Immunity Test.....	12
4.7. For Surge Test.....	12
4.8. For Injected Currents Susceptibility Test.....	12
4.9. For Magnetic Field Immunity Test.....	12
4.10. For Voltage Dips and Interruptions Test.....	12
5. POWER LINE CONDUCTED EMISSION TEST.....	13
5.1. Block Diagram of Test Setup.....	13
5.2. Test Standard.....	13
5.3. Power Line Conducted Emission Limit.....	13
5.4. EUT Configuration on Test.....	13
5.5. Operating Condition of EUT.....	14
5.6. Test Procedure.....	14
5.7. Test Result.....	14
6. RADIATED EMISSION TEST.....	15
6.1. Open Site Setup Diagram.....	15
6.2. Test Standard.....	15
6.3. Radiated Emission Limit.....	15
6.4. EUT Configuration on Test.....	15
6.5. Operating Condition of EUT.....	16
6.6. Test Procedure.....	16
6.7. Test Results.....	16
7. HARMONIC CURRENT EMISSION TEST.....	17
7.1. Block Diagram of Test Setup.....	17
7.2. Test Standard and Limit.....	17
7.3. Test Procedure.....	18



7.4. Test Results	18
8. VOLTAGE FLUCTUATIONS & FLICKER TEST	19
8.1. Block Diagram of Test Setup	19
8.2. Test Standard	19
8.3. Operating Condition of EUT	19
8.4. Test Data	19
8.5. Test Results	19
9. ELECTROSTATIC DISCHARGE TEST	20
9.1. Block Diagram of ESD Test Setup	20
9.2. Test Standard	20
9.3. Severity Levels and Performance Criterion	20
9.4. EUT Configuration on Test	20
9.5. Operating Condition of EUT	20
9.6. Test Procedure	21
9.7. Test Results	21
10. RF FIELD STRENGTH SUSCEPTIBILITY TEST	23
10.1. R/S Test Setup	23
10.2. Test Standard	23
10.3. Severity Levels and Performance Criterion	23
10.4. EUT Configuration on Test	24
10.5. Operating Condition of EUT	24
10.6. Test Procedure	24
10.7. Test Results	24
11. ELECTRICAL FAST TRANSIENT/BURST TEST	26
11.1. EFT Test Setup	26
11.2. Test Standard	26
11.3. Severity Levels and Performance Criterion	26
11.4. EUT Configuration on Test	26
11.5. Operating Condition of EUT	26
11.6. Test Procedure	27
11.7. Test Results	27
12. SURGE TEST	29
12.1. Surge Test Setup	29
12.2. Test Standard	29
12.3. Severity Levels and Performance Criterion	29
12.4. EUT Configuration on Test	29
12.5. Operating Condition of EUT	29
12.6. Test Procedure	30
12.7. Test Results	30
13. INJECTED CURRENTS SUSCEPTIBILITY TEST	32
13.1. Block Diagram of Test AC Mains Setup	32
13.2. Test Standard	32
13.3. Severity Levels and Performance Criterion	32
13.4. EUT Configuration on Test	32
13.5. Operating Condition of EUT	32
13.6. Test Procedure	33
13.7. Test Results	33
14. VOLTAGE DIPS AND INTERRUPTIONS TEST	35



14.1. Voltage Dips and Interruptions Test Setup	35
14.2. Test Standard.....	35
14.3. Severity Levels and Performance Criterion	35
14.4. EUT Configuration on Test.....	35
14.5. Operating Condition of EUT.....	35
14.6. Test Procedure.....	36
14.7. Test Result.....	36
APPENDIX I	38
APPENDIX II.....	41
APPENDIX III	44



TEST REPORT DECLARATION

Applicant	:	SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.
Address	:	5th Floor B3, B1 B2 B3 Building, 2nd Nanchang Industrial Park, Xixiang Street, Baoan District, Shenzhen, China
EUT Description	:	INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY
Model Number	:	PS300-H1VXX,PS250-H1VXX, PS200-H1VXX (XX Stands for DC Output Voltage 05,12,24,36,48) (Note: The series products have the same circuit diagram, PCB layout and functionality. The differences are the model name and appearance, so, we select PS300-H1VXX to test.)



Test Standards:

EN 55032:2015/AC:2016,
EN 61000-3-2:2014 & EN 61000-3-3:2013
EN 55024:2010+A1:2015
(EN 61000-4-2:2009, EN 61000-4-3:2006+A1:2008+A2:2010,
EN 61000-4-4:2012, EN 61000-4-5:2014,
EN 61000-4-6:2014, EN 61000-4-8:2010, EN 61000-4-11:2004)

The EUT described above is tested by BST Technology Co., Ltd. EMC Laboratory to determine the maximum emissions from the EUT and ensure the EUT to be compliance with the immunity requirements of the EUT. BST Technology Co., Ltd. EMC Laboratory is assumed full responsibility for the accuracy of the test results. Also, this report shows that the EUT technically complies with the 2014/30/EU directive and its amendment requirements.

The test report is valid for above tested sample only and shall not be reproduced in part without written approval of the laboratory.

Prepared by :

Grace

Assistant

Tested by:

Jane.zhu

Test Engineer

Reviewer :

Ding

Supervisor

Approved & Authorized Signer :



Jack. Shu / Manager



1. TEST RESULTS SUMMARY

Table 1 Test Results Summary

Test Items	Test Results
Power Line Conducted Emission Test	PASS
Radiated Emission Test	PASS
Harmonic Current Emission Test	PASS
Voltage Fluctuations & Flicker Test	PASS
Electrostatic Discharge Test	PASS
RF Field Strength Susceptibility Test	PASS
Electrical Fast Transient/Burst Test	PASS
Surge Test	PASS
Injected Currents Susceptibility Test	PASS
Voltage Dips And Interruptions Test	PASS



2. GENERAL INFORMATION

2.1. Report information

- 2.1.1. This report is not a certificate of quality; it only applies to the sample of the specific product/equipment given at the time of its testing. The results are not used to indicate or imply that they are application to the similar items. In addition, such results must not be used to indicate or imply that BST approves recommends or endorses the manufacture, supplier or use of such product/equipment, or that BST in any way guarantees the later performance of the product/equipment.
- 2.1.2. The sample/s mentioned in this report is/are supplied by Applicant, BST therefore assumes no responsibility for the accuracy of information on the brand name, model number, origin of manufacture or any information supplied.
- 2.1.3. Additional copies of the report are available to the Applicant at an additional fee. No third part can obtain a copy of this report through BST, unless the applicant has authorized BST in writing to do so.

2.2. Measurement Uncertainty

Available upon request.




3. PRODUCT DESCRIPTION

3.1. EUT Description

Description	:	INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY
Applicant	:	SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD. 5th Floor B3, B1 B2 B3 Building, 2nd Nanchang Industrial Park, Xixiang Street, Baoan District, Shenzhen, China
Manufacturer	:	SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD. 5th Floor B3, B1 B2 B3 Building, 2nd Nanchang Industrial Park, Xixiang Street, Baoan District, Shenzhen, China
Model Number	:	PS300-H1VXX, PS250-H1VXX, PS200-H1VXX (XX Stands for DC Output Voltage 05,12,24,36,48)

3.2. Block Diagram of EUT Configuration



3.3. Operating Condition of EUT

Test mode : ON

3.4. Test Conditions

Temperature: 23-26℃

Relative Humidity: 55-68 %

3.5. Modifications

No modification was made.



3.6. Abbreviations

AC	Alternating Current
AMN	Artificial Mains Network
DC	Direct Current
EM	ElectroMagnetic
EMC	ElectroMagnetic Compatibility
EUT	Equipment Under Test
IF	Intermediate Frequency
RF	Radio Frequency
rms	root mean square
EMI	Electromagnetic Interference
EMS	Electromagnetic Susceptibility

3.7. Performance Criterion

Criterion A: The equipment shall continue to operate as intended without operator intervention. No degradation of performance or loss of function is allowed below a performance level specified by the manufacturer when the equipment is used as intended.

Criterion B: After the test, the equipment shall continue to operate as intended without operator intervention. No degradation of performance or loss of function is allowed, after the application of the phenomena below a performance level specified by the manufacturer, when the equipment is used as intended.

Criterion C: Loss of function is allowed, provided the function is self-recoverable, or can be restored by the operation of the controls by the user in accordance with the manufacturer's instructions.



4. TEST EQUIPMENT USED

4.1. For Conducted Emission Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Test Receiver	Rohde & Schwarz	ESHS30	828985/018	Jun. 01, 17	1 Year
2.	Pulse Limiter	Rohde & Schwarz	ESH3-Z2	100006	Jun. 01, 17	1 Year
3.	L.I.S.N.	Rohde & Schwarz	ESH2-Z5	834549/005	Jun. 01, 17	1 Year
4.	Conical	Emtek	N/A	N/A	N/A	N/A
5.	Voltage Probe	Schwarzbeck	TK9416	N/A	Jun. 01, 17	1 Year
6.	Coaxial Switch	Anritsu	MP59B	6100214550	Jun. 01, 17	1 Year

4.2. For Radiated Emission Measurement

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Spectrum Analyzer	ANRITSU	MS2661C	6200140915	Jun. 01, 17	1 Year
2.	Test Receiver	Rohde&Schwarz	ESC830	828982/018	Jun. 01, 17	1 Year
3.	Bilog Antenna	Schwarzbeck	VULB9163	142	Jun. 01, 17	1 Year
4.	50 Coaxial Switch	Anritsu Corp	MP59B	6100237248	Jun. 01, 17	1 Year
5.	Cable	Schwarzbeck	AK9513	ACRX1	Jun. 01, 17	1 Year
6.	Cable	Rosenberger	N/A	FR2RX2	Jun. 01, 17	1 Year
7.	Cable	Schwarzbeck	AK9513	CRRX2	Jun. 01, 17	1 Year
8.	Cable	Schwarzbeck	AK9513	CRRX2	Jun. 01, 17	1 Year
9.	Signal Generator	HP	864A	3625U00573	Jun. 01, 17	1 Year

4.3. For Harmonic / Flicker Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Power Frequency test system	HAEFELY	PHF555	080419-03	Jun. 01, 17	1 Year

4.4. For Electrostatic Discharge Immunity Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	ESD Tester	HAEFELY	PSD 1600	H911'292	Jun. 02, 17	1 Year

4.5. For RF Strength Susceptibility Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Signal Generator	HP	8648A	3633A02081	Jun. 03,17	1 Year
2.	Amplifier	A&R	500A100	17034	NCR	NCR
3.	Amplifier	A&R	100W/1000M1	17028	NCR	NCR
4.	Isotropic Field Monitor	A&R	FM2000	16829	NCR	NCR
5.	Isotropic Field Probe	A&R	FLW220100	16755	Jun. 03, 17	1 Year
6.	Biconic Antenna	EMCO	3108	9507-2534	NCR	NCR
7.	Log-periodic Antenna	A&R	AT1080	16812	NCR	NCR
8.	PC	N/A	486DX2	N/A	N/A	N/A



4.6. For Electrical Fast Transient/Burst Immunity Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Burst Tester	HAEFELY	PEFT 4010	080981-16	Jun. 01, 17	1 Year

4.7. For Surge Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Surge Tester	HAEFELY	PSURGE4.1	080107-04	Jun. 01, 17	1 Year

4.8. For Injected Currents Susceptibility Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Simulator	EMTEST	CWS 500C	0900-12	Jun. 01, 17	1 Year
2.	CDN	EMTEST	CDN-M2	510010010010	Jun. 01, 17	1 Year
3.	VDN	EMTEST	CDN-M3	0900-11	Jun. 01, 17	1 Year
4.	Injection Clamp	EMTEST	F-2031-23MM	368	Jun. 01, 17	1 Year
5.	Attenuator	EMTEST	ATT6	0010222a	Jun. 01, 17	1 Year

4.9. For Magnetic Field Immunity Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
1.	Magnetic Field Tester	HEAFELY	MAG100.1	083858-10	Jun. 01, 17	1 Year


4.10. For Voltage Dips and Interruptions Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Cal. Interval
2.	Dips Tester	HEAFELY	PLINE 1610	083732-18	Jun. 01, 17	1 Year



5. POWER LINE CONDUCTED EMISSION TEST

5.1. Block Diagram of Test Setup



5.2. Test Standard

EN 55032:2015/AC:2016

5.3. Power Line Conducted Emission Limit

Frequency MHz	Limits dB(μV)	
	Quasi-peak Level	Average Level
0.15 ~ 0.50	66 ~ 56*	56 ~ 46*
0.50 ~ 5.00	56	46
5.00 ~ 30.00	60	50

Notes: 1. *Decreasing linearly with logarithm of frequency.

2. The lower limit shall apply at the transition frequencies.

5.4. EUT Configuration on Test

The following equipments are installed on conducted emission test to meet EN55032 requirement and operating in a manner, which tends to maximize its emission characteristics in a normal application.

5.4.1. EUT Information

Model Number : PS300-H1VXX

Serial Number : N/A

Manufacturer : SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.



5.5. Operating Condition of EUT

5.5.1. Setup the EUT and simulators as shown in Section 5.1.

5.5.2. Turn on the power of all equipments.

5.5.3. Let the EUT work in test modes (ON) and test it.

5.6. Test Procedure

The EUT is put on the ground and connected to the AC mains through a Artificial Mains Network (AMN). This provided 50ohm-coupling impedance for the tested equipments. Both sides of AC line are checked to find out the maximum conducted emission levels according to the EN55032 regulations during conducted emission test.

The bandwidth of the test receiver (R&S Test Receiver ESHS30) is set at 10KHz.


The frequency range from 150 KHz to 30 MHz is investigated. and all the scanning waveform is put in **Appendix I**.

5.7. Test Result

PASS.

6. RADIATED EMISSION TEST

6.1. Open Site Setup Diagram



6.2. Test Standard

EN 55032:2015/AC:2016

6.3. Radiated Emission Limit

All emanations from a Class B computing devices or system, including any network of conductors and apparatus connected thereto, shall not exceed the level of field strengths specified below:

FREQUENCY (MHz)	DISTANCE (Meters)	FIELD STRENGTHS LIMITS (dB μ V/m)
30 ~ 230	3	40
230 ~ 1000	3	47

Note:(1) The tighter limit shall apply at the edge between two frequency bands.

(2) Distance refers to the distance in meters between the measuring instruments antenna and the closed point of any part of the EUT.

6.4. EUT Configuration on Test

The EN55032 Class B regulations test method must be used to find the maximum emission during radiated emission test.



6.5. Operating Condition of EUT

- 6.5.1. Setup the EUT as shown on Section 6.1.
- 6.5.2. Turn on the power of all equipments.
- 6.5.3. Let the EUT work in test mode and measure it.

6.6. Test Procedure

The EUT is placed on a turn table which is 0.8 meter above ground. The turn table can rotate 360 degrees to determine the position of the maximum emission level. The EUT is set 3 meters away from the receiving antenna which is mounted on a antenna tower. The antenna can move up and down between 1 to 4 meters to find out the maximum emission level. Broadband antenna (calibrated by dipole antenna) are used as a receiving antenna. Both horizontal and vertical polarization of the antenna are set on test. The bandwidth setting on the test receiver (R&S TEST RECEIVER ESCS20) is 120 KHz. The EUT is tested in Semi-Anechoic Chamber. and all the scanning waveform is put in **Appendix II.**


6.7. Test Results

PASS.



7. HARMONIC CURRENT EMISSION TEST

7.1. Block Diagram of Test Setup



7.2. Test Standard and Limit

7.2.1. Test Standard

EN 61000-3-2:2014

7.2.2. Limits

Table 12 Harmonic Current Test Limit (Class A)

Harmonic order (n)	Maximum permissible harmonic current (A)
Odd harmonics	
3	2.30
5	1.14
7	0.77
9	0.40
11	0.33
13	0.21
$15 \leq n \leq 39$	$0.15 \times 15/n$
Even harmonics	
2	1.08
4	0.43
6	0.30
$8 \leq n \leq 40$	$0.23 \times 8/n$



7.3. Test Procedure

The power cord of the EUT is connected to the output of the test system. Turn on the Power of the EUT and use the test system to test the harmonic current level.

7.4. Test Results

PASS.



8. VOLTAGE FLUCTUATIONS & FLICKER TEST

8.1. Block Diagram of Test Setup

Same as Section 7.1..

8.2. Test Standard

EN 61000-3-3:2013

8.3. Operating Condition of EUT

Same as Section 7.3.. The power cord of the EUT is connected to the output of the test system. Turn on the power of the EUT and use the test system to test the harmonic current level.

Flicker Test Limit

Test items	Limits
Pst	1.0
dc	3.3%
dmax	4.0%
dt	Not exceed 3.3% for 500ms

8.4. Test Data

Flicker test Data

Model No.: PS300-H1VXX

Test Mode: 1


Items	Reading	Limit
dmax	0.02	4.0%
dc	0.03	3.3%
dt	0.05	Not exceed 3.3% for 500ms
Pst	0.001	1.0

8.5. Test Results

PASS.

9. ELECTROSTATIC DISCHARGE TEST

9.1. Block Diagram of ESD Test Setup



9.2. Test Standard

EN 55020:2007+A11:2011+A12:2016 (EN 61000-4-2:2009)

Severity Level 3 for Air Discharge at 8KV

Severity Level 2 for Contact Discharge at 4KV

9.3. Severity Levels and Performance Criterion

9.3.1. Severity level

Level	Test Voltage Contact Discharge (KV)	Test Voltage Air Discharge (KV)
1.	2	2
2.	4	4
3.	6	8
4.	8	15
X.	Special	Special

9.3.2. Performance criterion: B

9.4. EUT Configuration on Test

The configuration of EUT are listed in Section 5.4

9.5. Operating Condition of EUT

9.5.1. Setup the EUT as shown in Section 9.1.

9.5.2. Turn on the power of all equipments.

9.5.3. Let the EUT work in test mode (ON) and test it.



9.6. Test Procedure

9.6.1. Air Discharge:

This test is done on a non-conductive surfaces. The round discharge tip of the discharge electrode shall be approached as fast as possible to touch the EUT.

After each discharge, the discharge electrode shall be removed from the EUT.

The generator is then re-triggered for a new single discharge and repeated 10 times for each pre-selected test point. This procedure shall be repeated until all the air discharge completed.

9.6.2. Contact Discharge:

All the procedure shall be same as Section 9.6.1. except that the tip of the discharge electrode shall touch the EUT before the discharge switch is operated.

9.6.3. Indirect discharge for horizontal coupling plane

At least 20 single discharges shall be applied to the horizontal coupling plane, at points on each side of the EUT. The discharge electrode positions vertically at a distance of 0.1m from the EUT and with the discharge electrode touching the coupling plane.

9.6.4. Indirect discharge for vertical coupling plane

At least 20 single discharge shall be applied to the center of one vertical edge of the coupling plane. The coupling plane, of dimensions 0.5m X 0.5m, is placed parallel to, and positioned at a distance of 0.1m from the EUT. Discharges shall be applied to the coupling plane, with this plane in sufficient different positions that the four faces of the EUT are completely illuminated.

9.7. Test Results

PASS.

Please refer to the following page.



Electrostatic Discharge Test Results

Shenzhen BST Technology Co., Ltd.


Applicant	: SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.	Test Date	: Sep. 14, 2017
EUT	: INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY	Temperature	: 22 °C
M/N	: PS300-H1VXX	Humidity	: 50 %
Power Supply	: AC 230V/50Hz	Test Mode	: ON
Air Discharge: $\pm 8KV$ For each point positive 10 times and negative 10 times discharge.			
Contact Discharge: $\pm 4KV$			
Location	Kind A-Air Discharge C-Contact Discharge	Result	
Slots	A	PASS	
Ports	C	PASS	
HCP	C	PASS	
VCP	C	PASS	

Discharge should be considered on Contact and Air and Horizontal Coupling Plane (HCP) and Vertical Coupling Plane (VCP).



10.RF FIELD STRENGTH SUSCEPTIBILITY TEST

10.1.R/S Test Setup



10.2.Test Standard

EN 55024:2010+A1:2015 (EN 61000-4-3:2006+A1:2008+A2:2010)
Severity Level 2 at 3V / m

10.3.Severity Levels and Performance Criterion

10.3.1.Severity level

Level	Field Strength V/m
1.	1
2.	3
3.	10
X.	Special

10.3.2.Performance criterion : A



10.4.EUT Configuration on Test

The configuration of EUT are listed in Section 5.4

10.5.Operating Condition of EUT

Setup the EUT as shown in Section 10.1.. The operating condition of EUT are listed in section 3.3.

10.6.Test Procedure

The EUT and its simulators are placed on a turn table which is 0.8 meter above the ground. The EUT is set 3 meters away from the transmitting antenna which is mounted on an antenna tower. Both horizontal and vertical polarization of the antenna are set on test. Each of the four sides of EUT must be faced this transmitting antenna and measured individually.

In order to judge the EUT performance, a CCD camera is used to monitor the EUT.

All the scanning conditions are as follows :

Condition of Test	Remarks
1. Fielded Strength	3 V/m (Severity Level 2)
2. Radiated Signal	Modulated
3. Scanning Frequency	80 - 1000 MHz, 1.4 - 2.7 GHz
4. Sweeping time of radiated	0.0015 decade/s
5. Dwell Time	1 Sec.

10.7.Test Results

PASS.

Please refer to the following page.




RF Field Strength Susceptibility Test Results

Shenzhen BST Technology Co., Ltd.

Applicant	: SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.	Test Date	: Sep. 14, 2017
EUT	: INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY	Temperature	: 22 °C
M/N	: PS300-H1VXX	Humidity	: 50 %
Power Supply	: AC 230V/50Hz	Test Mode	: ON
		Frequency Range	: 80 MHz to 1000 MHz 1.4 GHz to 2.7 GHz
Modulation:	<input checked="" type="checkbox"/> AM <input type="checkbox"/> Pulse <input type="checkbox"/> none	1 KHz	80%
Criterion : A			
	Frequency Rang : 80 MHz to 1000 MHz, 1.4 GHz to 2.7 GHz		
Steps	1%	1%	
	Horizontal	Vertical	
Front	Pass	Pass	
Right	Pass	Pass	
Rear	Pass	Pass	
Left	Pass	Pass	

11.ELECTRICAL FAST TRANSIENT/BURST TEST

11.1.EFT Test Setup



11.2.Test Standard

EN 55024:2010+A1:2015 (EN 61000-4-4:2012)
Severity Level 2 at 1KV

11.3.Severity Levels and Performance Criterion

11.3.1.Severity level

Open Circuit Output Test Voltage $\pm 10\%$		
Level	On Power Supply Lines	On I/O (Input/Output) Signal data and control lines
1.	0.5 KV	0.25 KV
2.	1 KV	0.5 KV
3.	2 KV	1 KV
4.	4 KV	2 KV
X	Special	Special

11.3.2.Performance criterion : B

11.4.EUT Configuration on Test

The configuration of EUT are listed in Section 5.4.

11.5.Operating Condition of EUT

Setup the EUT as shown in Section 11.1.. The operating condition of EUT are listed in section 3.3.



11.6.Test Procedure

The EUT is put on the table which is 0.8 meter high above the ground. This reference ground plane shall project beyond the EUT by at least 0.1m on all sides and the minimum distance between the EUT and all other conductive structure, except the ground plane beneath the EUT, shall be more than 0.5m.

11.6.1.For input and output AC power ports:

The EUT is connected to the power mains by using a coupling device which couples the EFT interference signal to AC power lines. Both polarities of the test voltage should be applied during compliance test and the duration of the test is 2 mins.

11.6.2.For signal lines and control lines ports:

It's unnecessary to test.

11.6.3.For DC output line ports:

It's unnecessary to test.

11.7.Test Results

PASS.

Please refer to the following page.




Electrical Fast Transient/Burst Test Results

Shenzhen BST Technology Co., Ltd.

<i>Applicant</i> :		<i>SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.</i>				<i>Test Date</i> :		<i>Sep. 14, 2017</i>	
<i>EUT</i> :		<i>INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY</i>				<i>Temperature</i> :		<i>22 ℃</i>	
<i>M/N</i> :		<i>PS300-H1VXX</i>				<i>Humidity</i> :		<i>50 %</i>	
<i>Power Supply</i> :		<i>AC 230V/50Hz</i>				<i>Test Mode</i> :		<i>ON</i>	
<i>Inject Place : AC Mains</i>									
<i>Inject Line</i>	<i>Voltage KV</i>	<i>Inject Time(s)</i>	<i>Inject Method</i>	<i>Results</i>	<i>Inject Line</i>	<i>Voltage KV</i>	<i>Inject Time(s)</i>	<i>Inject Method</i>	<i>Results</i>
<i>L</i>	<i>±1</i>	<i>120</i>	<i>Direct</i>	<i>PASS</i>					
<i>N</i>	<i>±1</i>	<i>120</i>	<i>Direct</i>	<i>PASS</i>					
<i>L N</i>	<i>±1</i>	<i>120</i>	<i>Direct</i>	<i>PASS</i>					

12.SURGE TEST

12.1.Surge Test Setup



12.2.Test Standard

EN 55024:2010+A1:2015 (EN 61000-4-5:2014)
Severity Level 2 for Line to Neutral at 1.0KV

12.3.Severity Levels and Performance Criterion

12.3.1.Severity level

Severity Level	Open-Circuit Test Voltage KV
1	0.5
2	1.0
3	2.0
4	4.0
*	Special

Performance criterion : **B**

12.4.EUT Configuration on Test

The configuration of EUT are listed in Section 5.4

12.5.Operating Condition of EUT

12.5.1.Setup the EUT as shown in Section 12.1..

12.5.2.Turn on the power of all equipments.

12.5.3.Let the EUT work in test mode (ON) and test it.



12.6.Test Procedure

- 1) Setup the EUT and test generator as shown on Section 12.1.
- 2) For line to line coupling mode, provide a 0.5KV 1.2/50us voltage surge (at open-circuit condition) and 8/20us current surge to EUT selected points.
- 3) At least 5 positive and 5 negative (polarity) tests with a maximum 1/min repetition rate are conducted during test.
- 4) Different phase angles are done individually.
- 5) Record the EUT operating situation during compliance test and decide the EUT immunity criterion for above each test.

12.7.Test Results

PASS.

Please refer to the following page.




Surge Immunity Test Results

Shenzhen BST Technology Co., Ltd.

Applicant : SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.					Test Date : Sep. 14, 2017
EUT : INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY					Temperature : 22 °C
M/N : PS300-H1VXX					Humidity : 50 %
Power Supply : AC 230V/50Hz					Test Mode : ON
Location	Polarity	Phase Angle	No of Pulse	Pulse Voltage (KV)	Result
L-N, L-PE, N-PE	+	0	5	1.0	PASS
	+	90	5	1.0	PASS
	+	180	5	1.0	PASS
	+	270	5	1.0	PASS
	-	0	5	1.0	PASS
	-	90	5	1.0	PASS
	-	180	5	1.0	PASS
	-	270	5	1.0	PASS

13.INJECTED CURRENTS SUSCEPTIBILITY TEST

13.1.Block Diagram of Test AC Mains Setup



13.2.Test Standard

EN 55024:2010+A1:2015 (EN 61000-4-6:2014)
Severity Level 2 at 3 V (rms), 0.15MHz ~ 80MHz

13.3.Severity Levels and Performance Criterion

13.3.1.Severity level

Level	Field Strength V/m
1.	1
2.	3
3.	10
X	Special

13.3.2.Performance criterion: A

13.4.EUT Configuration on Test

The configuration of EUT are listed in Section 5.4

13.5.Operating Condition of EUT

Setup the EUT as shown in Section 13.1.. The operating condition of EUT are listed in section 3.3



13.6.Test Procedure

- 1) Set up the EUT, CDN and test generators as shown on Section 13.1.
- 2) Let the EUT work in test mode and test it.
- 3) The EUT are placed on an insulating support 0.8m high above a ground reference plane. CDN (coupling and decoupling device) is placed on the ground plane about 0.3m from EUT. Cables between CDN and EUT are as short as possible, and their height above the ground reference plane shall be between 30 and 50 mm (where possible).
- 4) The disturbance signal described below is injected to EUT through CDN.
- 5) The EUT operates within its operational mode(s) under intended climatic conditions after power on.
- 6) The frequency range is swept from 150KHz to 80MHz using 3V signal level, and with the disturbance signal 80% amplitude modulated with a 1KHz sine wave.
- 7) The rate of sweep shall not exceed 1.5×10^{-3} decades/s. Where the frequency is swept incrementally, the step size shall not exceed 1% of the start and thereafter 1% of the preceding frequency value.
- 8) Recording the EUT operating situation during compliance testing and decide the EUT immunity criterion.

13.7.Test Results

PASS.

Please refer to the following page.




Injected Currents Susceptibility Test Results

Shenzhen BST Technology Co., Ltd.

Applicant : SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.		Test Date : Sep. 14, 2017		
EUT : INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY		Temperature : 22 °C		
M/N : PS300-H1VXX		Humidity : 50 %		
Power Supply : AC 230V/50Hz		Test Mode : ON		
Frequency Range (MHz)	Injected Position	Strength	Criterion	Result
0.15 ~ 20	AC Line	3V(rms), Unmodulated	A	PASS
20 ~ 80	AC Line	3V(rms), Unmodulated	A	PASS

14. VOLTAGE DIPS AND INTERRUPTIONS TEST

14.1. Voltage Dips and Interruptions Test Setup



Remark: Combination wave generator and decoupling network are included in test generator.

14.2. Test Standard

EN 55024:2010+A1:2015 (EN 61000-4-11:2004)

14.3. Severity Levels and Performance Criterion

14.3.1. Severity level

Test Level %U _T	Voltage dip and short interruptions %U _T	Duration (in period)
0	100	250p
40	60	5p
70	30	0.5p

14.3.2. Performance criterion : C & B

14.4. EUT Configuration on Test

The configuration of EUT are listed in Section 5.4

14.5. Operating Condition of EUT

14.5.1. Setup the EUT as shown in Section 14.1.

14.5.2. Turn on the power of all equipments.

14.5.3. Let the EUT work in test mode (ON) and test it.



14.6.Test Procedure

- 1) Set up the EUT and test generator as shown on Section 14.1.
- 2) The interruptions is introduced at selected phase angles with specified duration.
- 3) Record any degradation of performance.

14.7.Test Result

PASS.

Please refer to the following page.




Voltage Dips And Interruptions Test Results

Shenzhen BST Technology Co., Ltd

<i>Applicant</i>	:	<i>SHENZHEN SANPU INTELLIGENT TECHNOLOGY CO.,LTD.</i>		<i>Test Date</i>	:	<i>Sep. 14, 2017</i>	
<i>EUT</i>	:	<i>INDOOR CONSTANT VOLTAGE SWITCHING POWER SUPPLY</i>		<i>Temperature</i>	:	<i>22 ℃</i>	
<i>M/N</i>	:	<i>PS300-H1VXX</i>		<i>Humidity</i>	:	<i>50 %</i>	
<i>Power Supply</i>	:	<i>AC 230V/50Hz</i>		<i>Test Mode</i>	:	<i>ON</i>	
<i>Test Level</i> <i>% U_T</i>		<i>Voltage Dips & Short Interruptions</i> <i>% U_T</i>	<i>Duration (in period)</i>	<i>Phase Angle</i>		<i>Criterion</i>	<i>Result</i>
<i>0</i>		<i>100</i>	<i>250P</i>	<i>0° ~360°</i>		<i>C</i>	<i>PASS</i>
<i>70</i>		<i>30</i>	<i>25P</i>	<i>0° ~360°</i>		<i>C</i>	<i>PASS</i>
<i>0</i>		<i>100</i>	<i>0.5P</i>	<i>0° ~360°</i>		<i>B</i>	<i>PASS</i>



APPENDIX I



Site : Shenzhen BST Technology Co.,Ltd.

Condition:

: RBW:9.000KHz VBW:30.000KHz


	Freq	Level	Limit	Over	Remark	Pol/Phase
	MHz	dBuV	Line	Limit	dB	
1 Max	0.176	30.4	54.7	-24.3	Average	LINE
2	0.274	18.4	51.0	-34.6	Average	LINE
3	1.552	15.0	46.0	-31.0	Average	LINE
4	4.822	8.6	46.0	-37.4	Average	LINE
5	13.841	8.5	50.0	-41.5	Average	LINE
6	26.418	9.4	50.0	-40.6	Average	LINE

Site : Shenzhen BST Technology Co.,Ltd.

Condition:

: RBW:9.000KHz VBW:30.000KHz

	Freq	Level	Limit	Over	Remark	Pol/Phase
	MHz	dBuV	Line	Limit	dB	
1 Max	0.164	49.0	65.3	-16.3	Peak	LINE
2	0.360	28.8	58.7	-29.9	Peak	LINE
3	0.890	27.7	56.0	-28.3	Peak	LINE
4	4.454	21.1	56.0	-34.9	Peak	LINE
5	13.841	24.3	60.0	-35.7	Peak	LINE
6	26.418	18.1	60.0	-41.9	Peak	LINE



Site : Shenzhen BST Technology Co.,Ltd.

Condition:

: RBW:9.000KHz VBW:30.000KHz

	Freq	Level	Limit	Over	Remark	Pol/Phase
	MHz	dBuV	Line	Limit	dB	
1 Max	0.174	30.8	54.8	-24.0	Average	NEUTRAL
2	0.348	15.0	49.0	-34.0	Average	NEUTRAL
3	1.610	14.2	46.0	-31.8	Average	NEUTRAL
4	5.221	8.3	50.0	-41.7	Average	NEUTRAL
5	13.695	7.5	50.0	-42.5	Average	NEUTRAL
6	26.139	9.8	50.0	-40.2	Average	NEUTRAL

Site : Shenzhen BST Technology Co.,Ltd.


Condition:

: RBW:9.000KHz VBW:30.000KHz

	Freq	Level	Limit	Over	Remark	Pol/Phase
	MHz	dBuV	Line	Limit	dB	
1 Max	0.153	50.8	65.8	-15.0	Peak	NEUTRAL
2	0.274	33.5	61.0	-27.5	Peak	NEUTRAL
3	1.519	24.4	56.0	-31.6	Peak	NEUTRAL
4	5.333	21.1	60.0	-38.9	Peak	NEUTRAL
5	14.364	23.2	60.0	-36.8	Peak	NEUTRAL
6	24.659	17.6	60.0	-42.4	Peak	NEUTRAL




APPENDIX II



Condition : EN55032 3m HORIZONTAL
: RBW:120.000KHz VBW:300.000KHz SWT:Auto

	Freq	Level	Remark	Pol/Phase	Limit	Over
	MHz	dBuV/m			Line	Limit
					dBuV/m	dB
1	32.834	27.9	Peak	HORIZONTAL	40.0	-12.1
2	114.515	20.5	Peak	HORIZONTAL	40.0	-19.5
3	250.301	26.4	Peak	HORIZONTAL	40.0	-13.6
4	460.528	40.4	Peak	HORIZONTAL	47.0	-6.6
5	601.427	38.2	Peak	HORIZONTAL	47.0	-8.8
6	942.131	37.3	Peak	HORIZONTAL	47.0	-9.7





APPENDIX III

Photo 1 General Appearance of the EUT




Photo 2 General Appearance of the EUT




Photo 3 General Appearance of the EUT




Photo 4 General Appearance of the EUT






Photo 5 Test scene



Photo 6 Test scene

